



ANR019 PROTEUS-III UART vs SPI

A COMPARISON

VERSION 1.0

MARCH 30, 2021

Revision history

Manual version	Notes	Date
1.0	<ul style="list-style-type: none">Initial version	March 2021

Abbreviations and abstract

Abbreviation	Name	Description
CLK	Clock	SPI line for the clock signal
CS	Chip Select	SPI line to select the slave device.
I/O	Input/output	Pinout description.
MISO	Master In Slave Out	SPI line for data transmission from slave to master.
MOSI	Master Out Slave In	SPI line for data transmission from master to slave.
Payload		The intended message in a frame / package.
RF	Radio frequency	Describes wireless transmission.
SPI	Serial Peripheral Interface	Allows the serial communication with the module.
UART	Universal Asynchronous Receiver Transmitter	Allows the serial communication with the module.
[HEX] 0xhh	Hexadecimal	All numbers beginning with 0x are hexadecimal numbers. All other numbers are decimal, unless stated otherwise.

Contents

1	Introduction	4
2	Proteus-III vs Proteus-III-SPI	5
2.1	Hardware facts	5
2.2	Application facts	5
2.3	What to choose now?	8
2.3.1	Prefer Proteus-III-SPI	8
2.3.2	Prefer Proteus-III	8
3	References	9
4	Important notes	10
4.1	General customer responsibility	10
4.2	Customer responsibility related to specific, in particular safety-relevant applications	10
4.3	Best care and attention	10
4.4	Customer support for product specifications	10
4.5	Product improvements	11
4.6	Product life cycle	11
4.7	Property rights	11
4.8	General terms and conditions	11
5	Legal notice	12
5.1	Exclusion of liability	12
5.2	Suitability in customer applications	12
5.3	Trademarks	12
5.4	Usage restriction	12
6	License terms	14
6.1	Limited license	14
6.2	Usage and obligations	14
6.3	Ownership	15
6.4	Firmware update(s)	15
6.5	Disclaimer of warranty	15
6.6	Limitation of liability	15
6.7	Applicable law and jurisdiction	16
6.8	Severability clause	16
6.9	Miscellaneous	16

1 Introduction

The Proteus-III is a Bluetooth® LE module based on the nRF52 Nordic Semiconductors SoC which presents various Bluetooth® LE and low power features. It provides a command based UART interface that allows the configuration and control by simple commands.

Besides of that, there is a second variant of the Proteus-III, the so called Proteus-III-SPI radio module that provides the functions of the Proteus-III via SPI interface.

This application note describes what are the key facts to be considered, when choosing between the UART variant Proteus-III and the SPI variant Proteus-III-SPI.




Figure 1: Module to host connection

2 Proteus-III vs Proteus-III-SPI

This chapter collects all the points that have to be considered, when choosing between Proteus-III and Proteus-III-SPI as interface to the Bluetooth® LE world.

2.1 Hardware facts

The Proteus-III and Proteus-III-SPI use the same hardware. Both share the same foot print and use the same pins. Only the UART pins of the Proteus-III are replaced by the SPI pins on the Proteus-III-SPI. Furthermore, the *WAKE_UP* pin on the Proteus-III-SPI has a shared function, as it is used as SPI interrupt pin in case the module has not been set to deep sleep mode. In case the module is sleeping, its function is to wake-up the radio module.




Figure 2: Pinout

Thus from hardware point of view, there is no difficulty to switch between Proteus-III and Proteus-III-SPI (also at a later stage in the development process of the end device).

2.2 Application facts

Except of UART- or SPI-specific features, the Proteus-III and Proteus-III-SPI share the same functions. Nevertheless, both radio modules behave a bit different. The differences are listed in the tables below:

	Proteus-III (UART)	Proteus-III-SPI (SPI slave)
End device layout	The host controller must provide a free UART interface, that must be connected only to the Proteus-III.	The host controller must provide a SPI interface with extra CS line and SPI interrupt line for the Proteus-III-SPI. Several SPI slaves may be connected to the SPI clock and data lines of the SPI master.
Software integration of the UART/SPI	Easy <ul style="list-style-type: none"> • configure the UART baud rate and flow control • communication can start 	Medium <ul style="list-style-type: none"> • configure the SPI data rate and the SPI mode • implement the SPI interrupt pin • check and adjust the allowed timings of the <i>SPI_CS</i> and <i>SPI_CLK</i> line • communication can start
Software integration of the module functions	Easy - Use the Proteus-III drivers ¹ from Wireless Connectivity SDK [1].	
Maximum data rate	1 MBaud (UART)	8 MBit (SPI)
Throughput [kByte/s]	1Mbit UART can be the bottleneck for high throughputs, in case the radio uses a fast setting <ul style="list-style-type: none"> • 42.9 (fastest mode: 2 Mbit radio, 8 ms connection interval, high throughput mode on, 1 MBaud UART) • 16 (fast mode: 2 Mbit radio, 30 ms connection interval, high throughput mode on, 1 MBaud UART) • 1.57 (default mode: 1 Mbit radio, 30 ms connection interval, high throughput mode off, 125 kBaud UART) 	Boost the throughput ² if the radio link is not the bottleneck <ul style="list-style-type: none"> • 64.3 (fastest mode: 2 Mbit radio, 8 ms connection interval, high throughput mode on, 8 Mbit SPI) • 16 (fast mode: 2 Mbit radio, 30 ms connection interval, high throughput mode on, 8 Mbit SPI) • 1.57 (default mode: 1 Mbit radio, 30 ms connection interval, high throughput mode off, 8 Mbit SPI)

Table 1: Comparison of the keyfacts - Part 1

¹For integration of the module drivers into the host microcontroller, the host's peripherals (i.e. UART, SPI) must be adapted in the "global" directory of the driver.

²A SPI with a datarate of 700 kBit or faster increases the throughput compared with a 1 MBaud UART, in case the radio is fast enough.

	Proteus-III (UART)	Proteus-III-SPI (SPI slave)
EMC		More sensitive due to higher data rate, and thus higher risk.
Available radio certifications	RED, FCC, IC, ARIB	RED, FCC, IC
Operation modes	Command mode and peripheral only mode (transparent UART)	Command mode only
Current consumption	<ul style="list-style-type: none"> • Lower, in case UART is switched off <ul style="list-style-type: none"> – by user in command mode – automatically in peripheral only mode if radio connection is closed • Low, otherwise 	<ul style="list-style-type: none"> • Lower, as SPI is only enabled if CS is active

Table 2: Comparison of the keyfacts - Part 2

2.3 What to choose now?

2.3.1 Prefer Proteus-III-SPI

Prefer the Proteus-III-SPI if one or several of the following points match your application

- You do not have a free UART interface available, but a SPI interface with free CS pin and SPI interrupt pin.
- You need the highest possible end-to-end throughput.



Be aware that the connection partner must be able to provide all features and dependencies for the chosen throughput, too.

- You need the lowest possible power consumption without reducing the radio performance (i.e. throughput, timing behaviour).



The most effective way to reduce the current consumption is to reduce the transmission power and increase the connection interval (slow down the radio performance).

2.3.2 Prefer Proteus-III

Prefer the Proteus-III (UART) if one or several of the following points match your application:

- None of the Proteus-III-SPI points matches your application.
- You need a simple wire interface that works with minimum configuration.
- You want to use a transparent UART interface to the reduce effort in your software development.
- You cannot use the fastest radio settings (i.e. 2 Mbit phy or 8 ms connection interval) due to backward compatibility reasons to older Bluetooth® LE versions and low cost devices.
- You cannot use large radio packets (243 bytes payload per radio frame, and up to 4 radio frames per connection interval) due to backward compatibility reasons to older Bluetooth® LE versions and low cost devices.

3 References

- [1] Würth Elektronik. Wireless Connectivity SDK - Radio module drivers in C-code. <https://github.com/WurthElektronik/WirelessConnectivity-SDK>.

4 Important notes

The following conditions apply to all goods within the wireless connectivity product range of Würth Elektronik eiSos GmbH & Co. KG:

4.1 General customer responsibility

Some goods within the product range of Würth Elektronik eiSos GmbH & Co. KG contain statements regarding general suitability for certain application areas. These statements about suitability are based on our knowledge and experience of typical requirements concerning the areas, serve as general guidance and cannot be estimated as binding statements about the suitability for a customer application. The responsibility for the applicability and use in a particular customer design is always solely within the authority of the customer. Due to this fact, it is up to the customer to evaluate, where appropriate to investigate and to decide whether the device with the specific product characteristics described in the product specification is valid and suitable for the respective customer application or not. Accordingly, the customer is cautioned to verify that the documentation is current before placing orders.

4.2 Customer responsibility related to specific, in particular safety-relevant applications

It has to be clearly pointed out that the possibility of a malfunction of electronic components or failure before the end of the usual lifetime cannot be completely eliminated in the current state of the art, even if the products are operated within the range of the specifications. The same statement is valid for all software sourcecode and firmware parts contained in or used with or for products in the wireless connectivity and sensor product range of Würth Elektronik eiSos GmbH & Co. KG. In certain customer applications requiring a high level of safety and especially in customer applications in which the malfunction or failure of an electronic component could endanger human life or health, it must be ensured by most advanced technological aid of suitable design of the customer application that no injury or damage is caused to third parties in the event of malfunction or failure of an electronic component.

4.3 Best care and attention

Any product-specific data sheets, manuals, application notes, PCN's, warnings and cautions must be strictly observed in the most recent versions and matching to the products firmware revisions. This documents can be downloaded from the product specific sections on the wireless connectivity homepage.

4.4 Customer support for product specifications

Some products within the product range may contain substances, which are subject to restrictions in certain jurisdictions in order to serve specific technical requirements. Necessary information is available on request. In this case, the field sales engineer or the internal sales person in charge should be contacted who will be happy to support in this matter.

4.5 Product improvements

Due to constant product improvement, product specifications may change from time to time. As a standard reporting procedure of the Product Change Notification (PCN) according to the JEDEC-Standard, we inform about major changes. In case of further queries regarding the PCN, the field sales engineer, the internal sales person or the technical support team in charge should be contacted. The basic responsibility of the customer as per section 4.1 and 4.2 remains unaffected. All wireless connectivity module driver software "wireless connectivity SDK" and its source codes as well as all PC software tools are not subject to the Product Change Notification information process.

4.6 Product life cycle

Due to technical progress and economical evaluation we also reserve the right to discontinue production and delivery of products. As a standard reporting procedure of the Product Termination Notification (PTN) according to the JEDEC-Standard we will inform at an early stage about inevitable product discontinuance. According to this, we cannot ensure that all products within our product range will always be available. Therefore, it needs to be verified with the field sales engineer or the internal sales person in charge about the current product availability expectancy before or when the product for application design-in disposal is considered. The approach named above does not apply in the case of individual agreements deviating from the foregoing for customer-specific products.

4.7 Property rights

All the rights for contractual products produced by Würth Elektronik eiSos GmbH & Co. KG on the basis of ideas, development contracts as well as models or templates that are subject to copyright, patent or commercial protection supplied to the customer will remain with Würth Elektronik eiSos GmbH & Co. KG. Würth Elektronik eiSos GmbH & Co. KG does not warrant or represent that any license, either expressed or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, application, or process in which Würth Elektronik eiSos GmbH & Co. KG components or services are used.

4.8 General terms and conditions

Unless otherwise agreed in individual contracts, all orders are subject to the current version of the "General Terms and Conditions of Würth Elektronik eiSos Group", last version available at www.we-online.com.

5 Legal notice

5.1 Exclusion of liability

Würth Elektronik eiSos GmbH & Co. KG considers the information in this document to be correct at the time of publication. However, Würth Elektronik eiSos GmbH & Co. KG reserves the right to modify the information such as technical specifications or functions of its products or discontinue the production of these products or the support of one of these products without any written announcement or notification to customers. The customer must make sure that the information used corresponds to the latest published information. Würth Elektronik eiSos GmbH & Co. KG does not assume any liability for the use of its products. Würth Elektronik eiSos GmbH & Co. KG does not grant licenses for its patent rights or for any other of its intellectual property rights or third-party rights.

Notwithstanding anything above, Würth Elektronik eiSos GmbH & Co. KG makes no representations and/or warranties of any kind for the provided information related to their accuracy, correctness, completeness, usage of the products and/or usability for customer applications. Information published by Würth Elektronik eiSos GmbH & Co. KG regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof.

5.2 Suitability in customer applications

The customer bears the responsibility for compliance of systems or units, in which Würth Elektronik eiSos GmbH & Co. KG products are integrated, with applicable legal regulations. Customer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of Würth Elektronik eiSos GmbH & Co. KG components in its applications, notwithstanding any applications-related information or support that may be provided by Würth Elektronik eiSos GmbH & Co. KG. Customer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences lessen the likelihood of failures that might cause harm and take appropriate remedial actions. The customer will fully indemnify Würth Elektronik eiSos GmbH & Co. KG and its representatives against any damages arising out of the use of any Würth Elektronik eiSos GmbH & Co. KG components in safety-critical applications.

5.3 Trademarks

AMBER wireless is a registered trademark of Würth Elektronik eiSos GmbH & Co. KG. All other trademarks, registered trademarks, and product names are the exclusive property of the respective owners.

5.4 Usage restriction

Würth Elektronik eiSos GmbH & Co. KG products have been designed and developed for usage in general electronic equipment only. This product is not authorized for use in equipment where a higher safety standard and reliability standard is especially required or where a failure of the product is reasonably expected to cause severe personal injury or death,

unless the parties have executed an agreement specifically governing such use. Moreover, Würth Elektronik eiSos GmbH & Co. KG products are neither designed nor intended for use in areas such as military, aerospace, aviation, nuclear control, submarine, transportation (automotive control, train control, ship control), transportation signal, disaster prevention, medical, public information network etc. Würth Elektronik eiSos GmbH & Co. KG must be informed about the intent of such usage before the design-in stage. In addition, sufficient reliability evaluation checks for safety must be performed on every electronic component, which is used in electrical circuits that require high safety and reliability function or performance. By using Würth Elektronik eiSos GmbH & Co. KG products, the customer agrees to these terms and conditions.

6 License terms

This License Terms will take effect upon the purchase and usage of the Würth Elektronik eiSos GmbH & Co. KG wireless connectivity products. You hereby agree that this license terms is applicable to the product and the incorporated software, firmware and source codes (collectively, "Software") made available by Würth Elektronik eiSos in any form, including but not limited to binary, executable or source code form.

The software included in any Würth Elektronik eiSos wireless connectivity product is purchased to you on the condition that you accept the terms and conditions of this license terms. You agree to comply with all provisions under this license terms.

6.1 Limited license

Würth Elektronik eiSos hereby grants you a limited, non-exclusive, non-transferable and royalty-free license to use the software and under the conditions that will be set forth in this license terms. You are free to use the provided Software only in connection with one of the products from Würth Elektronik eiSos to the extent described in this license terms. You are entitled to change or alter the source code for the sole purpose of creating an application embedding the Würth Elektronik eiSos wireless connectivity product. The transfer of the source code to third parties is allowed to the sole extent that the source code is used by such third parties in connection with our product or another hardware provided by Würth Elektronik eiSos under strict adherence of this license terms. Würth Elektronik eiSos will not assume any liability for the usage of the incorporated software and the source code. You are not entitled to transfer the source code in any form to third parties without prior written consent of Würth Elektronik eiSos.

You are not allowed to reproduce, translate, reverse engineer, decompile, disassemble or create derivative works of the incorporated Software and the source code in whole or in part. No more extensive rights to use and exploit the products are granted to you.

6.2 Usage and obligations

The responsibility for the applicability and use of the Würth Elektronik eiSos wireless connectivity product with the incorporated Firmware in a particular customer design is always solely within the authority of the customer. Due to this fact, it is up to you to evaluate and investigate, where appropriate, and to decide whether the device with the specific product characteristics described in the product specification is valid and suitable for your respective application or not.

You are responsible for using the Würth Elektronik eiSos wireless connectivity product with the incorporated Firmware in compliance with all applicable product liability and product safety laws. You acknowledge to minimize the risk of loss and harm to individuals and bear the risk for failure leading to personal injury or death due to your usage of the product.

Würth Elektronik eiSos' products with the incorporated Firmware are not authorized for use in safety-critical applications, or where a failure of the product is reasonably expected to cause severe personal injury or death. Moreover, Würth Elektronik eiSos' products with the incorporated Firmware are neither designed nor intended for use in areas such as military, aerospace, aviation, nuclear control, submarine, transportation (automotive control, train control, ship control), transportation signal, disaster prevention, medical, public information network etc. You shall inform Würth Elektronik eiSos about the intent of such usage before design-in stage. In certain customer applications requiring a very high level of safety and in which the malfunction or failure of an electronic component could endanger human life or

health, you must ensure to have all necessary expertise in the safety and regulatory ramifications of your applications. You acknowledge and agree that you are solely responsible for all legal, regulatory and safety-related requirements concerning your products and any use of Würth Elektronik eiSos' products with the incorporated Firmware in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by Würth Elektronik eiSos. YOU SHALL INDEMNIFY WÜRTH ELEKTRONIK EISOS AGAINST ANY DAMAGES ARISING OUT OF THE USE OF WÜRTH ELEKTRONIK EISOS' PRODUCTS WITH THE INCORPORATED FIRMWARE IN SUCH SAFETY-CRITICAL APPLICATIONS.

6.3 Ownership

The incorporated Firmware created by Würth Elektronik eiSos is and will remain the exclusive property of Würth Elektronik eiSos.

6.4 Firmware update(s)

You have the opportunity to request the current and actual Firmware for a bought wireless connectivity Product within the time of warranty. However, Würth Elektronik eiSos has no obligation to update a modules firmware in their production facilities, but can offer this as a service on request. The upload of firmware updates falls within your responsibility, e.g. via ACC or another software for firmware updates. Firmware updates will not be communicated automatically. It is within your responsibility to check the current version of a firmware in the latest version of the product manual on our website. The revision table in the product manual provides all necessary information about firmware updates. There is no right to be provided with binary files, so called "Firmware images", those could be flashed through JTAG, SWD, Spi-Bi-Wire, SPI or similar interfaces.

6.5 Disclaimer of warranty

THE FIRMWARE IS PROVIDED "AS IS". YOU ACKNOWLEDGE THAT WÜRTH ELEKTRONIK EISOS MAKES NO REPRESENTATIONS AND WARRANTIES OF ANY KIND RELATED TO, BUT NOT LIMITED TO THE NON-INFRINGEMENT OF THIRD PARTIES' INTELLECTUAL PROPERTY RIGHTS OR THE MERCHANTABILITY OR FITNESS FOR YOUR INTENDED PURPOSE OR USAGE. WÜRTH ELEKTRONIK EISOS DOES NOT WARRANT OR REPRESENT THAT ANY LICENSE, EITHER EXPRESS OR IMPLIED, IS GRANTED UNDER ANY PATENT RIGHT, COPYRIGHT, MASK WORK RIGHT, OR OTHER INTELLECTUAL PROPERTY RIGHT RELATING TO ANY COMBINATION, MACHINE, OR PROCESS IN WHICH THE WÜRTH ELEKTRONIK EISOS' PRODUCT WITH THE INCORPORATED FIRMWARE IS USED. INFORMATION PUBLISHED BY WÜRTH ELEKTRONIK EISOS REGARDING THIRD-PARTY PRODUCTS OR SERVICES DOES NOT CONSTITUTE A LICENSE FROM WÜRTH ELEKTRONIK EISOS TO USE SUCH PRODUCTS OR SERVICES OR A WARRANTY OR ENDORSEMENT THEREOF.

6.6 Limitation of liability

Any liability not expressly provided by Würth Elektronik eiSos shall be disclaimed.

You agree to hold us harmless from any third-party claims related to your usage of the Würth Elektronik eiSos' products with the incorporated Firmware, software and source code. Würth

Elektronik eiSos disclaims any liability for any alteration, development created by you or your customers as well as for any combination with other products.

6.7 Applicable law and jurisdiction

Applicable law to this license terms shall be the laws of the Federal Republic of Germany. Any dispute, claim or controversy arising out of or relating to this license terms shall be resolved and finally settled by the court competent for the location of Würth Elektronik eiSos' registered office.

6.8 Severability clause

If a provision of this license terms is or becomes invalid, unenforceable or null and void, this shall not affect the remaining provisions of the terms. The parties shall replace any such provisions with new valid provisions that most closely approximate the purpose of the terms.

6.9 Miscellaneous

Würth Elektronik eiSos reserves the right at any time to change this terms at its own discretion. It is your responsibility to check at Würth Elektronik eiSos homepage for any updates. Your continued usage of the products will be deemed as the acceptance of the change.

We recommend you to be updated about the status of new firmware and software, which is available on our website or in our data sheet and manual, and to implement new software in your device where appropriate.

By ordering a wireless connectivity product, you accept this license terms in all terms.

List of Figures

1	Module to host connection	4
2	Pinout	5
a	Proteus-III (UART)	5
b	Proteus-III-SPI (SPI slave)	5

List of Tables

1	Comparison of the keyfacts - Part 1	6
2	Comparison of the keyfacts - Part 2	7



more than you expect



**Internet
of Things**



**Monitoring
& Control**



**Automated Meter
Reading**

Contact:

Würth Elektronik eiSos GmbH & Co. KG
Division Wireless Connectivity & Sensors

Max-Eyth-Straße 1
74638 Waldenburg
Germany

Tel.: +49 651 99355-0
Fax.: +49 651 99355-69
www.we-online.com/wireless-connectivity

