

durabit™

swissbit®


Product Fact Sheet

**microSDHC
Memory Card
for Secure Boot on
Raspberry Pi**

**PS-45u DP Series
“Raspberry Edition”**

8GB / 32GB
UHS-I Interface, MLC

Date: May 25, 2020
Revision: 01



Product Summary

- **Capacities:** 8 GBytes, 32 GBytes
- **Form Factor:** Standard microSD Memory card form factor – 15.0mm x 11.0mm x 0.7mm (1.0mm)
- **Compliance:** Fully compliant with SD Memory Card specification 2.0 and 3.0 and MICRO SD Memory Card Addendum 4.00
- **Performance:**
 - SD Default speed, SD High speed, SD UHS-I
 - Read Performance: Sequential Read up to 17 MBytes/s, Random Read IOPS up to 800
 - Write Performance: Sequential Write up to 13 MBytes/s, Random Write IOPS up to 500
- **Operating Temperature Range:**
 - Industrial: -40 °C to 85 °C
- **Operating Voltage:** 2.7...3.6V normal operating voltage (Low-power CMOS technology)
- **Data Retention:** 10 Years @ Life Begin / 1 Year @ Life End

Product Features

- **Protecting Raspberry Pi boot loader** (works with Raspberry Pi 2 and 3B+)
- **Authentication** is performed during the Swissbit customized **pre-boot** phase to unlock access
- **Encrypting user data and boot code** with AES 256bit to protect licenses, know-how and IP
- **The boot image can be set as read-only** to prevent unauthorized modification
- Restricting the access to data on the card by various configurable **security policies**
 - PIN – check a PIN entered via keyboard
 - USB – check presence of a USB authentication device (requires an Swissbit USB PU-50n „Raspberry Edition“)
 - NET policy – check presence of an authentication server in the network (requires an additional RaspberryPi as a server)

Ordering Information

Product Type	Product Series	Capacity	Part Number	Usage
microSD	PS-45u DP "Raspberry Edition"	8 GBytes	SFSD8192N3PM1T0-I-GE-020-RPo	One microSD card (8GB or 32GB) is required
microSD	PS-45u DP "Raspberry Edition"	32 GBytes	SFSD032GN3PM1T0-I-HG-020-RPo	
USB nano	PU-50n DP "Raspberry Edition"	8 GBytes	SFU3008GC1PE2T0-I-GE-020-RPo	Optional – required for "USB policy"

SDK & documentation

The SDK and user documentation is available for download under www.swissbit.com/secure-boot-rpi.

Why Swissbit?

Swissbit strives to create innovative technologies for future market opportunities utilizing a highly skilled in-house research and development team. Swissbit maintains a marketing edge by continuing to manufacture world-class high quality memory and security products and providing customers with both high value and low cost of ownership achieved through efficient processes and procedures.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Swissbit](#):

[SFSD8192N3PM1TO-I-GE-020-RP0](#) [SFSD032GN3PM1TO-I-HG-020-RP0](#)