

Product data sheet

Specifications

SQUARE D



Circuit breaker accessory,
PowerPacT P, lug kit, mechanical,
1200A, 3/0 AWG to 500kcmil,
copper, qty 3

CU1200P25K

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Range of Product	PowerPact P
Product or Component Type	Mechanical lug
Accessory / separate part category	Connection accessory
Quantity per Set	Set of 3

Complementary

Line Rated Current	1200 A
Material	Copper
Mounting Mode	Unit mount
Location of connection	Downstream Upstream
AWG gauge	AWG 3/0...500 kcmil aluminium
Kcmil size	500 kcmil
Tightening torque	442.5 lbf.in (50 N.m) 0.1...0.4 in ² (95...240 mm ²) (AWG 3/0...500 kcmil)

Environment

Product Certifications	CSA UL
------------------------	-----------

Ordering and shipping details

Category	US10DE201250
Discount Schedule	ODE2
GTIN	3606486279526
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	7.87 in (20.0 cm)
Package 1 Width	7.87 in (20.0 cm)
Package 1 Length	7.87 in (20.0 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package weight(Lbs) 10.501 lb(US) (4.763 kg)

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant
California proposition 65	WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov
PVC free	Yes

Use Again

Repack and remanufacture

Take-back	No
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.