

Product data sheet

Specifications

SQUARE D



Relay Socket, Harmony 8501N, 11 tubular pins, single tiered screw clamp terminals, DIN rail/panel mount, 15A-300V AC

8501NR82

Product availability: Stock - Normally stocked in distribution facility

Main

[In] rated current 15 A 300 V AC

Complementary

mounting type	Panel DIN rail
electrical connection	Double tiered screw clamp terminals
package quantity	1
Width	1.7 in (43 mm)
Height	3.1 in (80 mm)
Depth	1.02 in (26 mm)

Ordering and shipping details

Category	US10CP221142
Discount Schedule	OCP2
GTIN	785901583868
Returnability	Yes
Country of origin	CN

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.10 in (2.794 cm)
Package 1 Width	1.80 in (4.572 cm)
Package 1 Length	3.20 in (8.128 cm)
Package weight(Lbs)	2.240 oz (63.503 g)

Contractual warranty

Warranty 18 months

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Carbon footprint (kg CO2 eq, Total Life cycle)

1

Use Better

Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

REACH Regulation

[REACH Declaration](#)

California proposition 65

WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

Circularity Profile

No need of specific recycling operations

Take-back

No