

# Product data sheet

## Characteristics

# AR8561

## APC NetShelter Cable Management, Cable Trough, Black, 597 x 191.4 x 317.4 mm



### Overview

Presentation	Trough system to route power distribution cabling across the top of a NetShelter SX Enclosure.
Lead time	Usually in Stock

### Main

Provided equipment	Installation guide 1 x 8 inch/20cm grounding strap
--------------------	---

### Physical

Color	Black
Height	7.54 in (19.14 cm)
Width	23.50 in (59.7 cm)
Depth	12.50 in (31.74 cm)
Net Weight	11.97 lb(US) (5.43 kg)
Mounting preference	No preference
Mounting Mode	Not rack-mountable

### Conformance

Product Certifications	UL Classified
------------------------	---------------

### Ordering and shipping details

GTIN	731304253945
Package weight(Lbs)	18.06 lb(US) (8.19 kg)

### Packing Units

Package 1 Height	12.40 in (31.5 cm)
Package 1 width	27.95 in (71 cm)
Package 1 Length	17.32 in (44 cm)

### Offer Sustainability

Sustainable offer status	Green Premium product
REACH Regulation	<a href="#">REACH Declaration</a>
REACH free of SVHC	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) <a href="#">EU RoHS Declaration</a>
Toxic heavy metal free	Yes

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

---

Mercury free	Yes
RoHS exemption information	 Yes
Take-back	Take-back program available

---

#### Contractual warranty

---

Warranty	2 years repair or replace
----------	---------------------------

---