

Product data sheet

Specifications



Harmony XB6, legend holder 24 x 28 mm for legend 8 x 21 mm unmarked

ZB6YD21

Main

Range of product	Harmony XB6
Accessory / separate part designation	Legend holder with blank legend
Accessory / separate part type	Legend holder
Accessory / separate part category	Marking accessories
Accessory / separate part destination	Ø 16 mm control and signalling units
Legend holder size	24 x 28 mm
Label dimensions	8 x 21 mm
Marking	unmarked on 1 white side, 1 yellow side background

Complementary

Quantity per set	Set of 10
Net weight	0.001 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	1.500 cm
Package 1 Width	3.500 cm
Package 1 Length	3.750 cm
Package 1 Weight	0.900 g
Unit Type of Package 2	BB1
Number of Units in Package 2	10
Package 2 Height	1.500 cm
Package 2 Width	3.500 cm
Package 2 Length	7.500 cm
Package 2 Weight	9.000 g
Unit Type of Package 3	S01
Number of Units in Package 3	200
Package 3 Height	15.000 cm
Package 3 Width	15.000 cm
Package 3 Length	40.000 cm

Package 3 Weight 354.000 g

Contractual warranty

Warranty 18 months



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Total lifecycle Carbon footprint

1

Use Better

Materials and Substances

Packaging made with recycled cardboard

Yes

Packaging without single use plastic

No

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

California proposition 65

WARNING: This product can expose you to chemicals including: Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to [www.P65Warnings.ca.gov](#)

Use Again

Repack and remanufacture

Take-back

No