

Product data sheet

Specifications



Terminal shrouds, TeSys Control, for V3 / V4

VZ9

Main

Range TeSys

Device short name VZ

Product or component type Terminal shroud

Accessory / separate part category Protection accessory

Product compatibility V3
V4

Poles description 3P

Complementary

Product weight 20 g

Packing Units

Unit Type of Package 1 PCE

Number of Units in Package 1 1

Package 1 Height 4.000 cm

Package 1 Width 7.000 cm

Package 1 Length 9.000 cm

Package 1 Weight 13.000 g

Unit Type of Package 2 S02

Number of Units in Package 2 60

Package 2 Height 15.000 cm

Package 2 Width 30.000 cm

Package 2 Length 40.000 cm

Package 2 Weight 1.115 kg

Contractual warranty

Warranty 18 months

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Total lifecycle Carbon footprint **29**

Environmental Disclosure [Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard **Yes**

Packaging without single use plastic **No**

[EU RoHS Directive](#) **Compliant with Exemptions**

SCIP Number **63dc4fbe-3f44-4801-881b-22a3bb8008d9**

REACH Regulation [REACH Declaration](#)

California proposition 65 **WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to [www.P65Warnings.ca.gov](#)**

Halogen-free status **Halogen free product**

PVC free **Yes**

Use Again

Repack and remanufacture

End of life manual availability **No need of specific recycling operations**

Take-back **No**

Technical Illustration

Assembly's dimensions

