

Product data sheet

Specifications



preformed cordset, Modicon M340,
40 way terminal, 2 x HE10
connector, 0.5m

BMXFCC053

Main

Range of product	Modicon X80
Accessory / separate part type	Preformed cordset
Accessory / separate part designation	Preformed cordset for Telefast Advantys ABE7 sub-bases
Accessory / separate part destination	For I/O module with 40-way connectors
Number of cables	2
Electrical connection	1 connector 40 ways 2 connectors HE10
Cable length	0.5 m

Complementary

Total number of wires	40
Wire section	0.324 mm²
Net weight	0.21 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.000 cm
Package 1 Width	20.000 cm
Package 1 Length	25.000 cm
Package 1 Weight	212.000 g
Unit Type of Package 2	S02
Number of Units in Package 2	9
Package 2 Height	15.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	2.210 kg

Contractual warranty

Warranty	18 months
----------	-----------

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint	
Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture	
Take-back	No