

# FLKM 50-PA-MODI-A500/P - Front adapter



2290669

<https://www.phoenixcontact.com/us/products/2290669>

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



VARIOFACE front adapter, for Schneider Electric Modicon A250, A350, A500, non-isolated with option for potential separation and separate voltage supply, 1 x 32 channels can be connected

## Commercial data

Item number	2290669
Packing unit	2 pc
Minimum order quantity	1 pc
Product key	DK231F
GTIN	4017918058166
Weight per piece (including packing)	105.95 g
Weight per piece (excluding packing)	82.156 g
Country of origin	DE

# FLKM 50-PA-MODI-A500/P - Front adapter



2290669

<https://www.phoenixcontact.com/us/products/2290669>

## Technical data

### Product properties

Product type	Front adapter
Insulation characteristics	
Overvoltage category	II
Pollution degree	2

### Electrical properties

Max. permissible operating voltage	< 50 V AC
	60 V DC
Max. permissible current	1 A (per path)
	2 A (per connection, supply via separate power supply)

### Connection data

#### Field level

Connection method	IDC/FLK pin strip
Number of connections	1
Number of positions	50
Pitch	2.54 mm

#### Supply

Connection method	Screw connection
Conductor cross-section rigid	0.14 mm <sup>2</sup> ... 1.5 mm <sup>2</sup>
Conductor cross-section flexible	0.14 mm <sup>2</sup> ... 1.5 mm <sup>2</sup>
Conductor cross-section AWG	26 ... 16

### Environmental and real-life conditions

#### Ambient conditions

Ambient temperature (operation)	-20 °C ... 50 °C
Ambient temperature (storage/transport)	-20 °C ... 70 °C

### Standards and regulations

Standards/regulations	IEC 60664
	IEC 60664A
	DIN VDE 0110
	DIN VDE 0160 (in parts)

### Mounting

Mounting position	any
-------------------	-----

### Notes

Notes on operation	For proper use, the specifications of the installation directive (see
--------------------	---

# FLKM 50-PA-MODI-A500/P - Front adapter



2290669

<https://www.phoenixcontact.com/us/products/2290669>

Downloads) must be observed. For applications or use with third-party products, the specifications, and the safety and warning instructions of the respective third-party manufacturer must also be met.

# FLKM 50-PA-MODI-A500/P - Front adapter




2290669

<https://www.phoenixcontact.com/us/products/2290669>

## Drawings

### Circuit diagram



# FLKM 50-PA-MODI-A500/P - Front adapter

2290669

<https://www.phoenixcontact.com/us/products/2290669>



## Classifications

### ECLASS

ECLASS-13.0	27242292
-------------	----------

# FLKM 50-PA-MODI-A500/P - Front adapter



2290669

<https://www.phoenixcontact.com/us/products/2290669>

## Environmental product compliance

China RoHS	
Environment friendly use period (EFUP)	EFUP-50
	An article-related China RoHS declaration table can be found in the download area for the respective article under "Manufacturer declaration". For all articles with EFUP-E, no China RoHS declaration table issued and required.
EU REACH SVHC	
REACH candidate substance (CAS No.)	No substance above 0.1 wt%

Phoenix Contact 2025 © - all rights reserved  
<https://www.phoenixcontact.com>

Phoenix Contact USA  
586 Fulling Mill Road  
Middletown, PA 17057, United States  
(+717) 944-1300  
[info@phoenixcon.com](mailto:info@phoenixcon.com)